



# 5G NR/4G LTE CPE

Quick Sales Guide

# Mobile broadband product portfolio

5G NR	
Outdoor	Router
	 <b>NR7701</b> 5G NR
	 <b>NR7501</b> 5G NR
	 <b>NR7305</b> 5G NR
	 <b>NR7303</b> 5G NR
	 <b>NR7302</b> 5G NR
Indoor	Router
	 <b>NR5731</b> 5G NR
	 <b>NR5307</b> 5G NR
	 <b>NR5331</b> 5G NR
	 <b>NR5103</b> 5G NR
	 <b>NR5103E</b> 5G NR
Portable	Router
	 <b>NR2301</b> 5G NR

**Cat. 4**



**NR7103**  
5G NR



**NR7102**  
5G NR



**NR5103EV2**  
5G NR



**LTE3202-M437**  
4G LTE

# Key features

Category	Cat.	Model	Key features
Outdoor CPE	5G NR	NR7701 	<ul style="list-style-type: none"> <li>• 3GPP Release 17 5G NR, up to 4.4 Gbps/550 Mbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>• Supports Sub-6 GHz NR 3CC with 200 MHz channel bandwidth</li> <li>• Standard 802.3af/at 2.5G PoE</li> <li>• Multiple APNs with VLAN mapping</li> <li>• Remote management via TR-069/TR-369 (TR-181 and TR-143 speed test) and web GUI</li> <li>• IP67 hardened enclosure with industrial grade components</li> </ul>
		NR7501 	<ul style="list-style-type: none"> <li>• 3GPP Release 16 5G NR, up to 7.5 Gbps/2.9 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>• Supports Sub-6 GHz &amp; mmWave aggregation</li> <li>• Built-in mmWave AiP (Antenna in Package) with Max. EIRP 50 dBm</li> <li>• Built-in Sub-6 GHz 4x4 MIMO, high-gain antennas of up to 12 dBi per element</li> <li>• Standard 802.3bt 5G PoE</li> <li>• Multiple APNs with VLAN mapping</li> <li>• Remote management via TR-069/TR-369 (TR-181 and TR-143 speed test) and web GUI</li> <li>• IP68 hardened enclosure with industrial grade components</li> </ul>
		NR7305 	<ul style="list-style-type: none"> <li>• 3GPP Release 16 5G NR, up to 7.01 Gbps/2.5 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>• Supports Sub-6 GHz NR 4CC with 300 MHz channel bandwidth</li> <li>• Built-in 4x4 MIMO, high-gain antennas of up to 9 dBi per element</li> <li>• Standard 802.3af/at 2.5G PoE</li> <li>• Multiple APNs with VLAN mapping</li> <li>• Remote management via TR-069/TR-369 (TR-181 and TR-143/TR-471 speed test) and web GUI</li> <li>• IP67 hardened enclosure with industrial grade components</li> </ul>
		NR7303 	<ul style="list-style-type: none"> <li>• 3GPP Release 15 5G NR, up to 4.67 Gbps/2.5 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>• Supports Sub-6 GHz NR 2CC with 200 MHz channel bandwidth</li> <li>• Built-in 4x4 MIMO, high-gain antennas of up to 9 dBi per element</li> <li>• Standard 802.3af/at 2.5G PoE</li> <li>• Multiple APNs with VLAN mapping</li> <li>• Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> <li>• IP67 hardened enclosure with industrial grade components</li> </ul>
		NR7302 	<ul style="list-style-type: none"> <li>• 3GPP Release 16 5G NR, up to 4.0 Gbps/550 Mbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>• Supports Sub-6 GHz NR 3CC with 200 MHz channel bandwidth</li> <li>• Built-in 4x4 MIMO, high-gain antennas of up to 9 dBi per element</li> <li>• Standard 802.3af/at 2.5G PoE</li> <li>• Multiple APNs with VLAN mapping</li> <li>• Remote management via TR-069/TR-369 (TR-181 and TR-471 speed test) and web GUI</li> <li>• IP67 hardened enclosure with industrial grade components</li> </ul>
		NR7103 	<ul style="list-style-type: none"> <li>• 3GPP Release 15 5G NR, up to 4.67 Gbps/2.5 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>• Supports Sub-6 GHz NR 2CC with 200 MHz channel bandwidth</li> <li>• Built-in 4x4 MIMO, high-gain antennas of up to 9 dBi per element</li> <li>• Standard 802.3af/at 2.5G PoE</li> <li>• Multiple APNs with VLAN mapping</li> <li>• Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> <li>• IP68 hardened enclosure with industrial grade components</li> </ul>
		NR7102 	<ul style="list-style-type: none"> <li>• 3GPP Release 15 5G NR, up to 5 Gbps/650 Mbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>• Built-in 4x4 MIMO, high-gain antennas of up to 9 dBi per element</li> <li>• Standard 802.3af/at 2.5G PoE</li> <li>• Multiple APNs with VLAN mapping</li> <li>• Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> <li>• IP68 hardened enclosure with industrial grade components</li> </ul>

Category	Cat.	Model	Key features
Indoor CPE	5G NR	NR5731  	<ul style="list-style-type: none"> <li>3GPP Release 17 5G NR, up to 4.0 Gbps/900 Mbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 3CC with 200 MHz channel bandwidth</li> <li>WiFi 7 (11be) 4x4+4x4 DBDC for superior performance and coverage</li> <li>One 2.5GbE &amp; three GbE ports for optimized bandwidth utilization</li> <li>Remote management via TR-069/TR-369 (TR-181 and TR-471 speed test) and web GUI</li> <li>PCR-plastic and easy refurbishment product design</li> </ul>
		NR5307  	<ul style="list-style-type: none"> <li>3GPP Release 16 5G NR, up to 7.0 Gbps/2.5 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 4CA with 300 MHz channel bandwidth</li> <li>WiFi 7 (11be) 4x4+4x4 DBDC for superior performance and coverage</li> <li>Two 2.5 Gbps LAN ports for optimized bandwidth utilization</li> <li>Remote management via TR-069/TR-369 (TR-181 and TR-471 speed test) and web GUI</li> <li>PCR-plastic and easy refurbishment case with Zyxel One App support</li> </ul>
		NR5331  	<ul style="list-style-type: none"> <li>3GPP Release 16 5G NR, up to 7.01 Gbps/2.5 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 4CA with 300 MHz channel bandwidth</li> <li>WiFi 7 (11be) 4x4+4x4 DBDC for superior performance and coverage</li> <li>One 2.5GbE &amp; three GbE ports for optimized bandwidth utilization</li> <li>Remote management via TR-069/TR-369 (TR-181 and TR-471 speed test) and web GUI</li> <li>PCR-plastic and easy refurbishment product design</li> </ul>
		NR5103  	<ul style="list-style-type: none"> <li>3GPP Release 15 5G NR, up to 4.67 Gbps/2.5 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 2CC with 200 MHz channel bandwidth</li> <li>WiFi 6 (11ax) 4x4+4x4 for superior performance and coverage</li> <li>Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> <li>Certified with EasyMesh R2</li> </ul>
		NR5103E  	<ul style="list-style-type: none"> <li>3GPP Release 15 5G NR, up to 4.67 Gbps/2.5 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 2CC with 200 MHz channel bandwidth</li> <li>WiFi 6 (11ax) 2x2+2x2 for superior performance and coverage</li> <li>Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> <li>Certified with EasyMesh R2</li> </ul>
		NR5103EV2  	<ul style="list-style-type: none"> <li>3GPP Release 15 5G NR, up to 4.67 Gbps/2.5 Gbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>Supports Sub-6 GHz NR 2CC with 200 MHz channel bandwidth</li> <li>WiFi 6 (11ax) 2x2+2x2 for superior performance and coverage</li> <li>Remote management via TR-069/TR-369 (TR-181 and TR-471 speed test) and web GUI</li> <li>Certified with EasyMesh R2</li> </ul>
Cat. 4		LTE3202-M437 	<ul style="list-style-type: none"> <li>3GPP Release 9 Cat. 4, up to 150/50 Mbps* (DL/UL)</li> <li>N300 WiFi with multiple simultaneous SSIDs</li> <li>Seamless switching between 4G and 3G</li> <li>Remote management via TR-069 (TR-181 and TR-143 speed test) and web GUI</li> </ul>
Portable CPE	5G NR	NR2301  	<ul style="list-style-type: none"> <li>3GPP Release 16 5G NR, up to 2.0 Gbps/650 Mbps* (DL/UL) with the support of NSA &amp; SA mode</li> <li>WiFi 6 (11ax) 2x2+2x2 DBDC for superior performance and coverage</li> <li>USB 3.1 type C Quick Charging</li> <li>Up to 10 hours working time with 2.4" LCD screen</li> <li>Two CRC9 external antenna connectors</li> </ul>

\* The maximum data rate is a theoretical value. The actual data rate depends on the operator.

\*\* All models support Zyxel Air app (iOS and Android)

# Frequency band comparison

## Outdoor CPE

Model	5G NR	NR7701	NR7501	NR7305	NR
Product name	5G NR Outdoor Router		5G NR Outdoor Router	5G NR Outdoor Router	5G
Ingress Protection Rating	IP67		IP68	IP67	IP6
5G NR	<b>Standard</b>	Rel. 17	Rel. 16	Rel. 16	Rel.
	<b>FDD</b>	n1, n3, n7, n8, n20, n28	n1, n3, n5, n7, n8, n20, n28	n1, n3, n5, n7, n8, n20, n28	n1,
4G LTE	<b>TDD</b>	n38, n40, n41, n75, n76, n77, n78	n38, n40, n41, n77, n78, n257, n258, n260, n261	n38, n40, n41, n75, n77, n78	n38
	<b>FDD</b>	B1, B3, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B20, B28, B32	B1,
DL CA	<b>TDD</b>	B38, B40, B41, B42, B43	B38, B40, B41, B42	B38, B40, B41, B42	B38
	5G NR: 3xCA 4G LTE: 5xCA		5G NR: 3xCA 4G LTE: 5xCA	5G NR: 4xCA 4G LTE: 5xCA	5G 4G
UL CA	5G NR: 2xCA (SA mode)		5G NR: 2xCA (SA mode)	5G NR: 2xCA (SA mode)	5G
	5G NR UL: 2x2 MIMO on n1/n3/n7/n38/n40/n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n8/n20/n28/n38/n40/n41/n75/n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/B8/B40/B38/B41/B42/B43	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n38/n40/n41/n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/B8/B40/B41/B42	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n38/n40/n41/n75/n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/B38/B40/B41/B42	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n38/n40/n41/n75/n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/B38/B40/B41/B42	5G 2x2 5G 4x4 n41 4G 4x4 B40
Modulation (DL/UL)	256-QAM/256-QAM		256-QAM/256-QAM	256-QAM/256-QAM	256
WiFi	<b>802.11n 2x2</b>	Yes*	Yes*	Yes*	Yes
Ethernet	<b>GbE LAN</b>	x1 (2.5GbE PoE)	x1 (10GbE PoE)	x1 (2.5GbE PoE)	x1 (
	<b>GbE WAN</b>	-	-	-	-
SIM	<b>Micro/Mini SIM slot</b>	Nano SIM	Micro SIM	Nano SIM	Micro
	<b>eSIM**</b>	Optional	Optional	Optional	Opt
Power	<b>DC input</b>	PoE 48 V	PoE 48 V	PoE 48 V	PoE

\* WiFi AP is used for management purpose only.

\*\* eSIM service is available upon customer request. Please contact us for more information on the availability of 5G FWA routers.

<b>NR7303</b>	<b>NR7302</b>	<b>NR7103</b>	<b>NR7102</b>
NR Outdoor Router	5G NR Outdoor Router	5G NR Outdoor Router	5G NR Outdoor Router
7	IP67	IP68	IP68
.15	Rel. 16	Rel. 15	Rel. 15
n3, n5, n7, n8, n20, n28	n1, n3, n5, n7, n8, n20, n28	n1, n3, n5, n7, n8, n20, n28	n1, n3, n5, n7, n8, n20, n28
n38, n40, n41, n77, n78	n38, n40, n41, n77, n78, n75	n38, n40, n41, n77, n78	n38, n40, n41, n77, n78
B3, B5, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B20, B28	B1, B3, B5, B7, B8, B20, B28
B3, B40, B41, B42	B38, B40, B41, B42	B38, B40, B41, B42	B38, B40, B41, B42
NR: 2xCA LTE: 5xCA	5G NR: 3xCA 4G LTE: 5xCA	5G NR: 2xCA 4G LTE: 5xCA	5G NR: EN-DC 4G LTE: 7xCA
NR: 2xCA (SA mode)	5G NR: 2xCA (SA mode)	5G NR: 2xCA (SA mode)	5G NR: 2xCA (SA mode)
NR UL: MIMO on n41/n77/n78	5G NR UL: 2x2 MIMO on n41/n77/n78	5G NR UL: 2x2 MIMO on n41/n77/n78	5G NR UL: 2x2 MIMO on n41/n77/n78
NR DL: MIMO on n1/n3/n7/n38/n40/ n77/n78	5G NR DL: 4x4 MIMO on n1/n3/n7/n38/n40/ n41/n77/n78	5G NR DL: 4x4 MIMO on n1/n3/n7/n38/ n40/n41/n77/n78	5G NR DL: 4x4 MIMO on n1/n3/n7/n20/n28/ n38/n40/n41/n77/n78
LTE DL: MIMO on B1/B3/B7/B32/B38/ B41/B42	4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/ B38/B40/B41/B42	4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/ B38/B40/B41/B42	4G LTE DL: 4x4 MIMO on B1/B3/B7/B40/B41/ B42
6-QAM/256-QAM	256-QAM/256-QAM	256-QAM/256-QAM	256-QAM/256-QAM
Yes*	Yes*	Yes*	Yes*
2.5GbE PoE	x1 (2.5GbE PoE)	x1 (2.5GbE PoE)	x1 (2.5GbE PoE)
-	-	-	-
Micro SIM	Micro SIM	Micro SIM	Micro SIM
Optional	Optional	-	-
PoE 48 V	PoE 48 V	PoE 48 V	PoE 48 V

# Frequency band comparison

## Indoor CPE

Model		5G NR		
		NR5731	NR5307	NR5331
<b>Product name</b>		5G NR Indoor Router	5G NR Indoor Router	5G NR Indoor Router
<b>5G NR</b>	<b>Standard</b>	Rel. 17	Rel. 16	Rel. 16
	<b>FDD</b>	n1, n3, n7, n8, n20, n28	n1, n3, n5, n7, n8, n20, n28	n1, n3, n5, n7, n8, n20, n28
<b>4G LTE</b>	<b>TDD</b>	n38, n40, n41, n75, n76, n77, n78	n38, n40, n41, n75, n77, n78	n38, n40, n41, n75, n77, n78
	<b>FDD</b>	B1, B3, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B20, B28, B32
<b>DL CA</b>	<b>TDD</b>	B38, B40, B41, B42, B43	B38, B40, B41, B42, B43	B38, B40, B41, B42, B43
		5G NR: 3xCA 4G LTE: 5xCA	5G NR: 4xCA 4G LTE: 5xCA	5G NR: 4xCA 4G LTE: 5xCA
<b>UL CA</b>		5G NR: 2xCA (SA mode)	5G NR: 2xCA (SA mode)	5G NR: 2xCA (SA mode)
<b>MIMO</b>		5G NR UL: 2x2 MIMO on n1/n3/n7/n38/n40/ n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n7/n8/n20/ n28/n38/n40/n41/n75/n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B7/B8/B40/ B38/B41/B42/B43	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n5/n7/n8/ n20/n28/n38/n40/n41/n75/ n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B5/B7/B8/ B20/B28/B32/B38/B40/B41/B42/ B43	5G NR UL: 2x2 MIMO on n41/n77/n78 5G NR DL: 4x4 MIMO on n1/n3/n5/n7/n8/ n20/n28/n38/n40/n41/n75/ n77/n78 4G LTE DL: 4x4 MIMO on B1/B3/B5/B7/B8/ B20/B28/B32/B38/B40/B41/B42/ B43
		256-QAM/256-QAM	256-QAM/256-QAM	256-QAM/256-QAM
<b>WiFi</b>	<b>802.11n 2x2</b>	-	-	-
	<b>802.11ac 2x2</b>	-	-	-
	<b>802.11ax 2x2</b>	-	-	-
	<b>802.11ax 4x4</b>	-	-	-
	<b>802.11be 4x4</b>	Yes	Yes	Yes
<b>Ethernet</b>	<b>Number of users</b>	up to 64	up to 64	up to 64
	<b>GbE LAN</b>	x2 (2.5GbE)	x2 (2.5GbE)	x3
<b>Phone</b>	<b>GbE WAN</b>	x1 (reuse LAN 1)	x1 (reuse LAN 1)	x1 (2.5GbE)
	<b>VoIP</b>	-	-	-
	<b>Vo3G/VoLTE</b>	-	-	-
<b>SIM slot</b>	<b>Micro/Mini SIM slot</b>	Nano SIM	Nano SIM	Nano SIM
<b>Power</b>	<b>DC input</b>	Type-C PD	Type-C PD	Type-C PD

<b>NR5103</b>	<b>NR5103E</b>	<b>NR5103EV2</b>	<b>Cat. 4</b>
			<b>LTE3202-M437</b>
5G NR Indoor Router	5G NR Indoor Router	5G NR Indoor Router	4G LTE Indoor Router
Rel. 15	Rel. 15	Rel. 15	-
n1, n2, n5, n7, n8, n20, n28	n1, n3, n7, n8, n20, n28	n1, n3, n7, n8, n20, n28	-
n38, n40, n41, n77, n78	n38, n40, n41, n77, n78	n38, n40, n41, n77, n78	-
B1, B3, B5, B7, B8, B28	B1, B3, B5, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B20, B28, B32	B1, B3, B5, B7, B8, B20, B28 (28a)
B38, B40, B41, B42	B34, B38, B39, B40, B41, B42, B43	B34, B38, B39, B40, B41, B42, B43	B38, B40, B41
5G NR: 2xCA 4G LTE: 5xCA	5G NR: 2xCA 4G LTE: 5xCA	5G NR: 2xCA 4G LTE: 5xCA	-
5G NR: 2xCA (SA mode)	5G NR: 2xCA (SA mode)	5G NR: 2xCA (SA mode)	-
5G NR UL: 2x2 MIMO on n41/n77/n78	5G NR UL: 2x2 MIMO on n41/n77/n78	5G NR UL: 2x2 MIMO on n41/n77/n78	-
5G NR DL: 4x4 MIMO on n1/n3/n7/n38/ n40/n41/n77/n78	5G NR DL: 4x4 MIMO on n1/n3/n7/n38/ n40/n41/n77/n78	5G NR DL: 4x4 MIMO on n1/n3/n7/n38/ n40/n41/n77/n78	-
4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/ B38/B40/B41/B42	4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/ B38/B40/B41/B42	4G LTE DL: 4x4 MIMO on B1/B3/B7/B32/ B38/B40/B41/B42	-
256-QAM/256-QAM	256-QAM/256-QAM	256-QAM/256-QAM	64-QAM/16-QAM
-	-	-	Yes
-	-	-	Yes
-	Yes	Yes	-
Yes	-	-	-
-	-	-	-
up to 64	up to 64	up to 64	up to 16
x2 (2.5GbE)	x2 (2.5GbE)	x2 (1GbE)	-
x1 (reuse LAN 1)	x1 (reuse LAN 1)	x1 (reuse LAN 1)	-
-	-	-	-
-	-	-	-
Micro SIM	Micro SIM	Micro SIM	Micro SIM
DC 12 V	DC 12 V	DC 12 V	DC 12 V

# Frequency band comparison

## Portable CPE

<b>Model</b>	<b>5G NR</b>	
	NR2301	
<b>Product name</b>	5G NR Portable Router	
<b>5G NR</b>	<b>Standard</b>	Rel. 16
	<b>FDD</b>	n1, n3, n7, n8, n20, n28
<b>4G LTE</b>	<b>TDD</b>	n41, n77, n78
	<b>FDD</b>	B1, B2, B3, B5, B7, B8, B20, B28
<b>TDD</b>		B38, B40, B41, B42, B43
<b>DL CA</b>	5G NR 2x CA 4G LTE 5x CA	
<b>UL CA</b>	5G NR: 2x CA(SA mode)	
<b>MIMO</b>	5G NR UL: 2x2 MIMO on n41/n77/n78	
	5G NR DL: 4x4 MIMO on n1/n3/n5/n7/n8/n20/n28/n38/n40/n41/n75/n77/n78	
<b>Modulation (DL/UL)</b>	4G LTE DL: 4x4 MIMO on B1/B3/B5/B7/B8/B20/B28/B32/B38/B40/B41/B42/B43	
	256-QAM/256-QAM	
<b>WiFi</b>	<b>802.11n 2x2</b>	-
	<b>802.11ac 2x2</b>	-
	<b>802.11ac 4x4</b>	-
	<b>802.11ax 2x2</b>	Yes
	<b>802.11ax 4x4</b>	-
	<b>Number of users</b>	up to 32
<b>Ethernet</b>	<b>GbE LAN</b>	-
	<b>GbE WAN</b>	-
<b>Phone</b>	<b>VoIP</b>	-
	<b>Vo3G/VoLTE</b>	-
<b>SIM slot</b>	<b>Micro/Mini SIM slot</b>	Micro SIM
<b>Power</b>	<b>DC input</b>	DC 9 V
<b>Battery</b>	<b>Capacity</b>	5300 mAh



## Corporate headquarters

### Zyxel Communications Corp.

Tel: +886 3 578 3942  
Fax: +886 3 578 2439  
Email: sales@zyxel.com.tw  
<https://service-provider.zyxel.com>

## EMEA

### Zyxel Armenia

Tel: +374 96 584 694

### Zyxel Azerbaijan

Email: sales.sp@zyxel.ru

### Zyxel Benelux

Tel: +31 23 555 3689  
Fax: +31 23 557 8492

### Zyxel Bulgaria

Tel: +3592 4443343

### Zyxel Czech Republic

Tel: +420 241 091 350  
Hotline: +420 241 774 665  
Fax: +420 241 091 359

### Zyxel Denmark

Tel: +45 39 55 07 00  
Fax: +45 39 55 07 07

### Zyxel Egypt

Email: da.sales@zyxel.com.tw

### Zyxel Finland

Tel: +358 9 4780 8400

### Zyxel France

Tel: +33 (0) 4 72 52 97 97  
Fax: +33 (0) 4 72 52 19 20

### Zyxel Germany

Tel: +49 (0) 2405 6909 0  
Fax: +49 (0) 2405 6909 99

### Zyxel Hungary & SEE

Tel: +36 1 848 0690

### Zyxel Iberia

Tel: +34 911 792 100

### Zyxel Israel

Email: da.sales@zyxel.com.tw

### Zyxel Italy

Tel: +39 011 2308000

### Zyxel Kazakhstan

Tel: +7 727 350 5683  
Fax: +7 727 2590 689

### Zyxel Norway

Tel: +47 22 80 61 80  
Fax: +47 22 80 61 81

### Zyxel Poland

Tel: +48 223 338 250  
Hotline: +48 226 521 626  
Fax: +48 223 338 251

### Zyxel Romania

Tel: +40 31 0809 888  
Fax: +40 31 0809 890

### Zyxel Slovakia

Tel: +421 220 861 847  
Hotline: +421 220 861 848  
Fax: +421 243 193 990

### Zyxel Sweden

Tel: +46 8 55 77 60 60  
Fax: +46 8 55 77 60 61  
Email: isp@zyxel.eu

### Zyxel Spain

Tel: +34 911 792 100

### Zyxel Turkey

Tel: +90 212 314 18 00  
Fax: +90 212 220 25 26

### Zyxel UK

Tel: +44 (0) 118 9121 700  
Fax: +44 (0) 118 9797 277

### Zyxel Ukraine

Tel: +380 89 323 9959

## APAC

### Zyxel Australia

Email: apac.sales@zyxel.com.tw

### Zyxel India

Tel: +91 11 4760 8800  
Fax: +91 11 4052 3393  
Email: info@zyxel.in

### Zyxel Japan

Email: apac.sales@zyxel.com.tw

### Zyxel Malaysia

Email: apac.sales@zyxel.com.tw

### Zyxel Phillipine

Email: apac.sales@zyxel.com.tw

### Zyxel Singapore

Email: apac.sales@zyxel.com.tw

### Zyxel Taiwan (Taipei)

Tel: +886 2 2739 9889  
Fax: +886 2 8913 1896  
Email: sales\_tw@zyxel.com.tw

### Zyxel Thailand

Tel: +66 (0) 2831 5315  
Fax: +66 (0) 2831 5395  
Email: info@zyxel.co.th

### Zyxel Vietnam

Email: apac.sales@zyxel.com.tw

## North America

### Zyxel USA

Tel: +1 714 632 0882  
+1 800 255 4101 (free)  
Fax: +1 714 632 0858  
Email: keyaccount@zyxel.com

### Zyxel Canada

Tel: +1 714 632 0882  
+1 800 255 4101 (free)  
Fax: +1 714 632 0858  
Email: keyaccount@zyxel.com

## South America

### Zyxel Argentina

Email: sa.sales@zyxel.com.tw

### Zyxel Brazil

Tel: +55 (11) 3373 7470  
Fax: +55 (11) 3373 7510  
Email: comercial@zyxel.com.br

### Zyxel Bolivia

Email: sa.sales@zyxel.com.tw

### Zyxel Chile

Email: sa.sales@zyxel.com.tw

### Zyxel Colombia

Email: sa.sales@zyxel.com.tw

### Zyxel Ecuador

Email: sa.sales@zyxel.com.tw

### Zyxel Paraguay

Email: sa.sales@zyxel.com.tw

### Zyxel Peru

Email: sa.sales@zyxel.com.tw

### Zyxel Uruguay

Email: sa.sales@zyxel.com.tw

For more product information, visit us on the web at  
<https://www.zyxel.com/service-provider>

Copyright © 2024 Zyxel and/or its affiliates. All rights reserved.  
All specifications are subject to change without notice.

